

ATND1061LK **ATND1061DAN**

Beamforming Array Microphone

Notes on Firmware Release

Update details

Ver.1.4.1

Improvements

- We have solved a problem that network information could occasionally not be received.
- We have improved talker location estimation accuracy.

Notes on the Past Firmware Release

Ver.1.4.0

Added functions

- Login function has been added to Web Remote.
- Microphone can now restart from Web Remote.

Improvements

- We have improved accuracy in detecting the talker's position.
- IP address containing periods can now be entered by copying and pasting.
- The IP control command "Talker Position Notification" now supports TCP.
- We have fixed a problem that the elevation angle of room settings would reset to 0° when using "Recall Preset."
- We have fixed a problem that changing other settings became impossible when the voice lift setting was set to

Ver.1.3.1

Improvements

- When the protocol is set to "VISCA over IP" in the camera linking function, the port number can be changed.

Ver.1.3.0

Added functions

- We have added an output selection for coverage and priority beams when using the voice lift function.

Improvements

- We have made an improvement so it is easy to correct the detected talker position by setting the room reverberation to high or low.
- We have reduced the connection time between Digital Microphone Manager and the microphone and the preset saving time.
- We have improved a problem in which the ATND1061 could not be detected on the network by the Digital Microphone Manager or Locate application.

Notes on the Past Firmware Release

- We have changed the default values of the Command Link settings to Off.
- We have solved the problem of calling camera presets due to far-end audio while using both camera link and AEC.
- We have solved the problem of camera linking being disabled when “Settings&Maintenance” > “Camera” > “Enabled” is switched between ON and OFF during use of the camera linking function.
- The error message “[0220] (Camera communication error)” that appears when the camera is disconnected now disappears automatically when the camera is reconnected.
- We have changed the display of the IP address on the “Network” screen.

Ver.1.2.1

Improvements

- We have fixed a problem that caused some settings to be lost.
- We have improved a problem in which the device would restart at an unintended time during operation.
- We have fixed a problem in which the ATND1061 could not be detected on the network by the Digital Microphone Manager or Locate application.
- We have adjusted the microphone indicator lamp display.
- We have solved the problem of the microphone's mute status not matching the mute status of the Digital Microphone Manager when the microphone was restarted.

Ver.1.2.0

Added functions

- We have added the voice lift function.
- “Command Link” now supports IP control.

Improvements

- We have improved the marker display and the performance of the talker detection function.
- We have also made other minor improvements.

Ver.1.1.0

Added functions

- We have added the camera linking function with PTZ cameras.

Improvements

- We have improved the performance of the talker detection function.
- In the talker detection function, markers are no longer displayed outside the area.
- In the IP control, talker location notification command now judges no speech when an AEC reference input is made.
- We have also made other minor improvements.

Ver.1.0.4

Improvements

- We have resolved a bug where Command Link settings for the IR Remote would not work properly.
- We have improved the beamforming algorithm by way of increasing the accuracy of speaker direction recognition and optimizing Beam Sensitivity settings.
- We have also made other minor improvements.

Supported version

The firmware (Ver. 1.4.1) of this product is compatible with Digital Microphone Manager Ver. 1.5.0. When updating the firmware of this product, be sure to update Digital Microphone Manager.

Precautions

- Always download the latest firmware when performing firmware updates. Check our website (https://www.audio-technica.com/world_map/) for the latest information on firmware.
- Read the following procedures carefully when executing an update.
- None of the product's functions will be available while the update is in progress.
- While updating, do not disconnect any cables from the product.
- While updating, do not disconnect the LAN cable connected to the control device.
- If the update fails and the product does not start, perform a forced update procedure to recover.
- Contact your local Audio-Technica dealer if you cannot recover with a forced update.
- Device settings for the product are saved even when updating. However, just for good measure, we recommend saving them to a preset or writing down the setting values.

About the firmware update


Microphone firmware can be updated using the Web Remote or Digital Microphone Manager. Before starting the update, connect the microphone with the control device. See the user manual for information on how to connect the microphone.

Updating using Web Remote

1 Download the latest firmware from our website and unzip the compressed file.


- Save the unzipped file on your local disk or in a folder.

2 Launch Web Remote and click “Utilities” under “System Settings”.



3 Use the “Serial No.”, “Device Name”, and “Firmware Ver.” shown on the screen to determine whether the microphone is subject to an update.


4 Click “Browse”.



5 Select a file to be updated from the file selection screen.

6 Click “Update”.

About the firmware update



» The update will start. Once the update is complete, the microphone will automatically reboot.

7 Check the firmware version.

- Confirm that the update has completed correctly in "System Info".

8 Reset the microphone to the factory default settings.



- Due to additional firmware functions and improvement details, Web Remote may possibly display and function incorrectly after updating. If this occurs, delete your history and cache on your web browser.

Updating using Digital Microphone Manager

1 Download the latest firmware from our website and unzip the compressed file.


- Save the unzipped file on your local disk or in a folder.

2 Launch Digital Microphone Manager.

3 Select a microphone in the main area.

» The microphone settings screen appears.

4 Click the area in the red box.




» The Settings & Maintenance screen appears.

About the firmware update

5 Click “Utilities” under “System Settings”.

6 Use the “Serial Number”, “Device Name”, and “Firmware Version” shown on the screen to determine whether the microphone is subject to an update.

7 Click “Browse”.




Firmware Update

Serial Number	Device Name	Firmware Version
0	ATND1061	1.0.0

Browse Update

8 Select a file to be updated from the file selection screen.

9 Click “Update”.



Firmware Update

Serial Number	Device Name	Firmware Version
0	ATND1061	1.0.0

Browse ATND1061DANFW.BIN Update

» The update will start. Once the update is complete, the microphone will automatically reboot.

10 Check the firmware version.

- Confirm that the update has completed correctly in “System Info”.

11 Reset the microphone to the factory default settings.



- With the latest version of Digital Microphone Manager, firmware can also be downloaded from Digital Microphone Manager. When the “Download for firmware update” appears on the screen, click “Download” to download the latest firmware.

About the forced update

If interference such as a power outage occurs while the firmware is updating that causes the update to not finish correctly, an error may occur when the product is turned on and the product may not operate normally. If this happens, the microphone can be restored to normal operation by forcibly updating the firmware.

1 Set the IP address of the control device to which the microphone will be connected to static.

- The following settings will be configured if the microphone has a startup error due to a failure during the update.
IP Config Mode: Static
IP Address: 192.168.33.102
Subnet Mask: 255.255.255.000
- To connect the microphone to a network, set the IP address of your Windows PC/Mac to an address that can communicate with the address "192.168.33.102". (Example: 192.168.33.100)

2 Connect the control device to the same network as the microphone.

3 Launch the web browser of the control device.

4 Delete your web browser history and cache.

- Web Remote may possibly display and function incorrectly if you don't delete your history and cache on your web browser.

5 Enter the microphone's IP address, "192.168.33.102".

Emergency Update

Device Status

Serial No.	Device Name	Firmware Ver.
00000100	ATND-1061	0.0.18

ファイルを選択 選択されていません

Update

Staus: -

Elapsed time: -

» Web Remote will launch in forced update mode.

6 Select and open a file to be updated.

7 Click "Update".

About the forced update

Emergency Update

Device Status

Serial No.	Device Name	Firmware Ver.
00000100	ATND-1061	0.0.18

ファイルを選択 ATND1061DANFW.BIN

Update

Status: -

Elapsed time: -

» The update will start. Once the update is complete, the microphone will automatically reboot.
After the microphone restarts, the IP Config Mode will be switched to "Auto".

8 Check the firmware version on the Firmware Update screen of Web Remote or Digital Microphone Manager.

- Check the firmware version to confirm whether the microphone was updated correctly.

9 Reset the microphone to the factory default settings.



- Due to additional firmware functions and improvement details, Web Remote may possibly display and function incorrectly after updating. If this occurs, delete your history and cache on your web browser.

Software License Agreement

Software License Agreement of Audio-Technica Corporation

This Software License Agreement (hereinafter referred to as the "Agreement") is a legal agreement between you, the customer, and Audio-Technica Corporation ("Audio-Technica") with respect to the software downloaded from the website of Audio-Technica (hereinafter referred to as the "Software"). You shall, when downloading the Software from the Audio-Technica website, installing the downloaded Software, or using it, carefully read the following provisions without fail. You shall be considered to agree to this Agreement when you use the Software. You may not install and use the Software in the case where you do not agree to all the provisions of this Agreement.

Article 1. License and Copyright etc.

- (1) Audio-Technica shall grant to you the right to use the program and data file consisting of the Software and the upgraded programs and data file thereof, which can be provided to you with certain conditions in the future (hereinafter referred to as the "Licensed Program") within the scope specified in this Agreement.
- (2) The Licensed Program is protected by the copyright and treaty concerning the copyright and other laws and treaties concerning the intellectual property right. The ownership, copyright, and any and all other intellectual property rights to and in the Licensed Program shall vest in Audio-Technica or Audio-Technica's licensor.
- (3) The right to and in the data generated by using the Licensed Program shall vest in you.

Article 2. Scope of Use

The scope of your use of the Licensed Program shall be as stipulated below.

- (1) You may use the Licensed Program in your computer.
- (2) You may reproduce the Licensed Program only for the purpose of backing up the data input by you; provided, however, that the reproduction shall not be used simultaneously in any other computer, whether possessed by you or any third party, except when used to recover the backup data.

Article 3. Restriction of Use

You shall, when using the Licensed Program, comply with the following matters.

- (1) You may transfer the Licensed Program to any other computer possessed by you; provided, however, that in such a case the Licensed Program shall be completely removed from the computer from which the Licensed Program is transferred.
- (2) You shall not distribute or transmit the Licensed Program.
- (3) You shall not lend, lease, or pledge collateral on the Licensed Program.
- (4) You shall neither reverse-engineer, decompile, disassemble, modify, or alter the Licensed Program nor make software derived from the Software.

Article 4. Limitation of Warranty

(1) Audio-Technica shall in no event warrant, explicitly or implicitly, the Licensed Program's merchantability, fitness for a particular purpose, or non-infringement of third-party rights. Furthermore, Audio-Technica shall in no event warrant that the Licensed Program operates properly and shall in no event warrant that any failure or defect in the Licensed Program can be modified.

(2) Any and all information or advice provided by Audio-Technica, orally or in writing, etc., shall not be considered to provide a new warranty or expand the scope of the warranty specified in this article in any sense whatsoever.

Article 5. Limitation of Liability

(1) You shall be liable for any and all direct and indirect damages (such as loss of data, computer failure, cessation of business, and complaints from any third party) and risks arising out of the use of the Licensed Program.

(2) Audio-Technica shall, in no event, be liable to you or any other third party for any direct, indirect, special, incidental or consequential loss or damage including but not limited to any loss of business values, suspension of business, loss or damage arising out of computer failure, or any other commercial loss or damage.

Article 6. Assignment of Licensed Program

You may assign the right to use the Licensed Program to any third party; provided, however, that in this case you shall completely delete the Licensed Program from the recording media of your computer and shall not possess any reproduction of the Licensed Program, and the assignee shall agree to any and all provisions of this Agreement.

Article 7. Cancellation and Termination of This Agreement

(1) In the case where you violate any of the provisions of this Agreement, Audio-Technica may cancel this Agreement with immediate effect without demand.

(2) In the case where this Agreement is canceled, you shall completely delete the Licensed Program from the recording media of your computer and destroy the reproduction of the Licensed Program.

(3) Audio-Technica shall be exempt from any and all responsibilities for any damage, etc. which you or any third party suffer because it becomes impossible to use the Licensed Program as a result of the cancellation of this Agreement.

Article 8. Governing Law and Miscellaneous Provisions

(1) This Agreement shall be governed by the laws of Japan.

(2) It is agreed that any dispute arising in relation to this Agreement or the Licensed Program shall be subject to the jurisdiction of the Tokyo District Court or Tokyo Summary Court in the first instance, depending on the amount sued for.

株式会社オーディオテクニカ

〒194-8666 東京都町田市西成瀬2-46-1
www.audio-technica.co.jp

Audio-Technica Corporation

2-46-1 Nishi-naruse, Machida, Tokyo 194-8666, Japan
www.audio-technica.com
©2025 Audio-Technica Corporation
Global Support Contact: www.at-globalsupport.com

142420840-02-08

ver.1 2022.08.01
ver.8 2025.10.01